

## Female Crimp Extra Small Bore

- Extra small bore for 28 – 32 AWG.
- Crimp contacts are rear insertable.
- Mates with male connectors shown on pages 52, 54, 56, 58, 60, 63 and 64.
- Part numbers are for a housing and the equivalent number of contacts.
- Spare contacts available, see page 51.
- Versions also available for 22 – 28 AWG cable – see page 44.



DATAMATE J-TEK

WITHOUT JACKSCREWS	WITH JACKSCREWS								
<table border="1" style="background-color: #f4a460; width: 100%;"> <thead> <tr> <th colspan="2">CALCULATION</th> </tr> </thead> <tbody> <tr> <td><b>A</b></td> <td><math>B + 12</math></td> </tr> <tr> <td><b>B</b></td> <td>Total no. of contacts - 2</td> </tr> <tr> <td><b>C</b></td> <td><math>B + 7</math></td> </tr> </tbody> </table>		CALCULATION		<b>A</b>	$B + 12$	<b>B</b>	Total no. of contacts - 2	<b>C</b>	$B + 7$
CALCULATION									
<b>A</b>	$B + 12$								
<b>B</b>	Total no. of contacts - 2								
<b>C</b>	$B + 7$								

TOOLS	WIRE STRIPPING DETAILS
<p><b>Recommended Crimp Tool</b> – M22520/2-01  <b>Positioner</b> – T5747  <b>Contact Insertion/Removal Tool</b> – Z80-280                      See pages 87 to 89                      ➤ Instruction sheets available at <a href="http://www.harwin.com/downloads/instructions">www.harwin.com/downloads/instructions</a></p>	

### HOW TO ORDER

M80 - 4 E1 XX XX FX

<b>SERIES CODE</b>	M80
<b>TYPE</b>	4 E1
<b>TOTAL NO. OF CONTACTS</b>	XX XX FX

JACKSCREW	
<b>00</b>	Without Jackscrews
<b>F1</b>	With Hexagonal Slotted Jackscrews
<b>F2</b>	With Hex Socket Jackscrews

FINISH	
<b>05</b>	Gold <span style="float: right; border: 1px solid black; border-radius: 50%; padding: 2px;">Pd</span>
<b>42</b>	Gold + Tin <span style="float: right; border: 1px solid black; border-radius: 50%; padding: 2px;">Pd</span>

Even numbers only

All dimensions in mm.