

RFM7N35/7N40

RFP7N35/7N40

N-Channel Enhancement Mode
Power Field Effect Transistors

August 1991

Features

- 7A, 350V and 400V
- $r_{DS(on)} = 0.75\Omega$
- SOA is Power-Dissipation Limited
- Nanosecond Switching Speeds
- Linear Transfer Characteristics
- High Input Impedance
- Majority Carrier Device


Description

The RFM7N35 and RFM7N40 and the RFP7N35 and RFP7N40 are n-channel enhancement-mode silicon-gate power field-effect transistors designed for applications such as switching regulators, switching converters, motor drivers, relay drivers, and drivers for high-power bipolar switching transistors requiring high speed and low gate-drive power. These types can be operated directly from integrated circuits.


The RFM-series types are supplied in the JEDEC TO-204AA steel package and the RFP-series types in the JEDEC TO-220AB plastic package.

Packages

TO-204AA




TO-220AB



Terminal Diagram

N-CHANNEL ENHANCEMENT MODE



Absolute Maximum Ratings ($T_C = 25^\circ C$), Unless Otherwise Specified

	RFM7N35	RFM7N40	RFP7N35	RFP7N40	UNITS
Drain-Source Voltage	V_{DSS}	350	400	350	V
Drain-Gate Voltage ($R_{GS} = 1m\Omega$)	V_{DGR}	350	400	350	V
Continuous Drain Current					
RMS Continuous	I_D	7	7	7	A
Pulsed Drain Current	I_{DM}	15	15	15	A
Gate-Source Voltage	V_{GS}	± 20	± 20	± 20	V
Maximum Power Dissipation					
$T_C = +25^\circ C$	P_D	100	100	75	W
Above $T_C = +25^\circ C$, Derate Linearly		0.8	0.8	0.6	$W/^\circ C$
Operating and Storage Junction	T_J, T_{STG}	-55 to +150	-55 to +150	-55 to +150	$^\circ C$
Temperature Range					

Specifications RFM7N35, RFM7N40, RFP7N35, RFP7N40

ELECTRICAL CHARACTERISTICS, At Case Temperature (T_c)=25°C unless otherwise specified

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	LIMITS				UNITS	
			RFM7N35 RFP7N35		RFM7N40 RFP7N40			
			Min.	Max.	Min.	Max.		
Drain-Source Breakdown Voltage	V_{DSS}	$I_D=1\text{ mA}$ $V_{GS}=0$	350	—	400	—	V	
Gate-Threshold Voltage	$V_{GS(\text{th})}$	$V_{GS}=V_{DS}$ $I_D=1\text{ mA}$	2	4	2	4	V	
Zero-Gate Voltage Drain Current	I_{DSS}	$V_{DS}=280\text{ V}$	—	1	—	—	μA	
		$V_{DS}=320\text{ V}$	—	—	—	1		
		$T_c=125^\circ\text{C}$ $V_{DS}=280\text{ V}$ $V_{DS}=320\text{ V}$	—	50	—	—		
Gate-Source Leakage Current	I_{GSS}	$V_{GS}=\pm 20\text{ V}$ $V_{DS}=0$	—	100	—	100	nA	
Drain-Source On Voltage	$V_{DS(\text{on})^a}$	$I_D=3.5\text{ A}$ $V_{GS}=10\text{ V}$	—	2.63	—	2.63	V	
		$I_D=7\text{ A}$ $V_{GS}=10\text{ V}$	—	10	—	10		
Static Drain-Source On Resistance	$r_{DS(\text{on})^a}$	$I_D=3.5\text{ A}$ $V_{GS}=10\text{ V}$	—	0.75	—	0.75	Ω	
Forward Transconductance	g_{fs}^a	$V_{DS}=10\text{ V}$ $I_D=3.5\text{ A}$	2	—	2	—	mho	
Input Capacitance	C_{iss}	$V_{DS}=25\text{ V}$ $V_{GS}=0\text{ V}$ $f=1\text{ MHz}$	—	1600	—	1600	pF	
Output Capacitance	C_{oss}		—	300	—	300		
Reverse-Transfer Capacitance	C_{rss}		—	200	—	200		
Turn-On Delay Time	$t_d(\text{on})$	$V_{DS}=200\text{ V}$ $I_D=3.5\text{ A}$ $R_{gen}=R_{gs}=50\Omega$ $V_{GS}=10\text{ V}$	16(typ)	45	16(typ)	45	ns	
Rise Time	t_r		54(typ)	75	54(typ)	75		
Turn-Off Delay Time	$t_d(\text{off})$		170(typ)	250	170(typ)	250		
Fall Time	t_f		62(typ)	100	62(typ)	100		
Thermal Resistance Junction-to-Case	R_{\thetaJC}	RFM7N35, RFM7N40	—	1.25	—	1.25	$^\circ\text{C/W}$	
		RFP7N35, RFP7N40	—	1.67	—	1.67		

SOURCE-DRAIN DIODE RATINGS AND CHARACTERISTICS

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	LIMITS				UNITS	
			RFM7N35 RFP7N35		RFM7N40 RFP7N40			
			Min.	Max.	Min.	Max.		
Diode Forward Voltage	V_{SD}^a	$I_{SD}=3.5\text{ A}$	—	1.4	—	1.4	V	
Reverse Recovery Time	t_{rr}	$I_F=4\text{ A}$ $dI/dt=100\text{ A}/\mu\text{s}$	870 (typ)				ns	

^aPulsed: Pulse duration=300 μs max., duty cycle=2%.




Fig. 1 - Maximum safe operating areas for all types.




Fig. 2 - Power dissipation vs. case temperature derating curve for all types.




Fig. 3 - Typical normalized gate threshold voltage as a function of junction temperature for all types.




Fig. 4 - Normalized drain-to-source on resistance as a function of junction temperature for all types.





Fig. 5 - Typical transfer characteristics for all types.

RFM7N35, RFM7N40, RFP7N35, RFP7N40



**Fig. 6 - Normalized switching waveforms for constant gate-current.
Refer to Harris application notes AN-7254 and AN-7260**




Fig. 7 - Typical saturation characteristics for all types.




Fig. 8 - Typical drain-to-source on resistance as a function of drain current for all types.




Fig. 9 - Capacitance as a function of drain-to-source voltage for all types.




Fig. 10 - Typical forward transconductance as a function of drain current for all types.




Fig. 11 - Switching time test circuit.