



Male connectors, straight

Identification	Number of contacts	Contact length [mm] mating side	termination side	Part number	Contact configuration
Type C	55	8.2	3.7	17 03 055 1201 <b>17 03 055 2201</b>	<p>Diagram showing a 4x11 grid of contacts labeled 'A'. The grid is labeled 'z' through 'f' on the right and '11' through '1' at the bottom. A small side-view diagram of the connector is shown to the right.</p>
Type C	77	8.2/ 11.2	3.7	17 03 077 1201 <b>17 03 077 2201</b>	<p>Diagram showing a 5x11 grid of contacts. The top row is labeled 'C', and the remaining four rows are labeled 'A'. The grid is labeled 'z' through 'f' on the right and '11' through '1' at the bottom. A small side-view diagram of the connector is shown to the right.</p>
Type C	55	9.7	3.7	17 03 055 1202 <b>17 03 055 2202</b>	<p>Diagram showing a 4x11 grid of contacts labeled 'B'. The grid is labeled 'z' through 'f' on the right and '11' through '1' at the bottom. A small side-view diagram of the connector is shown to the right.</p>
Type C	77	9.7/ 11.2	3.7	17 03 077 1202 <b>17 03 077 2202</b>	<p>Diagram showing a 5x11 grid of contacts. The top row is labeled 'C', the middle three rows are labeled 'B', and the bottom row is labeled 'C'. The grid is labeled 'z' through 'f' on the right and '11' through '1' at the bottom. A small side-view diagram of the connector is shown to the right.</p>
Type C	55	8.2	13.0	17 03 055 1401 <b>17 03 055 2401</b>	<p>Diagram showing a 4x11 grid of contacts labeled 'K'. The grid is labeled 'z' through 'f' on the right and '11' through '1' at the bottom. A small side-view diagram of the connector is shown to the right.</p>
Type C	66	8.2/ 11.2	13.0/ 16.0	17 03 066 1001 <b>17 03 066 2001</b>	<p>Diagram showing a 5x11 grid of contacts. The top four rows are labeled 'K' and the bottom row is labeled 'T'. The grid is labeled 'z' through 'f' on the right and '11' through '1' at the bottom. A small side-view diagram of the connector is shown to the right.</p>