



SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT
SINGLE PHASE	240	60	0-240	5.0	1.20	7.0	1.68	CW	1-4	---	4-3
								CCW	1-4	---	1-3
<small>UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS HOLES ANGLES DRAFT UNITS .XX .0005 .002 1° 1-1/2° IN [mm] MATERIAL: ALL DIMENSIONS APPLY AFTER PLATING</small>											
<small>THE INFORMATION AND DESIGN DISCLOSED HEREIN WAS ORIGINATED BY AND IS THE PROPERTY OF STACO ENERGY PRODUCTS CO., WHICH RESERVES ALL PATENT, PROPRIETARY, DESIGN, MANUFACTURING, REPRODUCTION, USE AND SALE RIGHTS THEREIN, AND TO ANY ARTICLE DISCLOSED THEREIN EXCEPT TO THE EXTENT RIGHTS ARE EXPRESSLY GRANTED TO OTHERS. THE FOREGOING DOES NOT APPLY TO VENDOR PROPRIETARY PARTS.</small>											
DRAWN BY		DATE		FIRST USED ON		DO NOT SCALE DWG.		STACO ENERGY PRODUCTS CO. <small>A Components Corporation of Ameresco Company 302 Gadsden Boulevard Dayton, Ohio 45403 USA</small>			
S.A. SMITH		9/25/97				CAGE CODE 83008		DWG. NO. 031-3260 SHEET 1 OF 1			
CHECKER		DATE		WEIGHT APPROX. 9 LBS		SCALE 1=1					
ENGINEER		DATE		SCALE							