

ZENER DIODES

Zener Type No.	Zener Voltage at I_{ZT}		Max. Zener Impedance @ I_{ZT} Ohms	Zener Voltage Tolerance	Power Rating	Device Package
	Volts	@ mA				
1N4728	3.3	76.0	10.0	No Suffix = 10% Suffix A = 5%	1 watt	DO-41
1N4729	3.6	69.0	10.0		"	"
1N4730	3.9	64.0	9.0		"	"
1N4731	4.3	58.0	9.0	" "	"	"
1N4732	4.7	53.0	8.0	" "	"	"
1N4733	5.1	49.0	7.0	" "	"	"
1N4734	5.6	45.0	5.0	" "	"	"
1N4735	6.2	41.0	2.0	" "	"	"
1N4736	6.8	37.0	3.5	" "	"	"
1N4737	7.5	34.0	4.0	" "	"	"
1N4738	8.2	31.0	4.5	" "	"	"
1N4739	9.1	28.0	5.0	" "	"	"
1N4740	10.0	25.0	7.0	" "	"	"
1N4741	11.0	23.0	8.0	" "	"	"
1N4742	12.0	21.0	9.0	" "	"	"
1N4743	13.0	19.0	10.0	" "	"	"
1N4744	15.0	17.0	14.0	" "	"	"
1N4745	16.0	15.5	16.0	" "	"	"
1N4746	18.0	14.0	20.0	" "	"	"
1N4747	20.0	12.5	22.0	" "	"	"
1N4748	22.0	11.5	23.0	" "	"	"
1N4749	24.0	10.5	25.0	" "	"	"
1N4750	27.0	9.5	35.0	" "	"	"
1N4751	30.0	8.5	40.0	" "	"	"
1N4752	33.0	7.5	45.0	" "	"	"
1N4753	36.0	7.0	50.0	" "	"	"
1N4754	39.0	6.5	60.0	" "	"	"
1N4755	43.0	6.0	70.0	" "	"	"
1N4756	47.0	5.5	80.0	" "	"	"
1N4757	51.0	5.0	95.0	" "	"	"
1N4758	56.0	4.5	110.0	" "	"	"
1N4759	62.0	4.0	125.0	" "	"	"
1N4760	68.0	3.7	150.0	" "	"	"
1N4761	75.0	3.3	175.0	" "	"	"
1N4762	82.0	3.0	200.0	" "	"	"
1N4763	91.0	2.8	250.0	" "	"	"
1N4764	100.0	2.5	350.0	" "	"	"