





Dual JFETs

N Channel

Device	V _p		G _{fs} (mmho)		V _{GS1-2} V _{DS} (mV) Max	Drift (μV/C) ΔV _{GS} Max	I _{SS} Match %	G _{fs} Match %	Package
	(V) Min	Max	Min	Max					
2N3955	1	4.5	1	3	10	25	5	5	TO-71
2N3956	1	4.5	1	3	15	50	5	5	TO-71
2N3958	1	4.5	1	3	25	100	15	15	TO-71
2N5197	0.7	4.0	1	4	5	10	5	3	TO-71
2N5564	0.5	3	7.5	12.5	5	10	5	5	TO-71
2N5565	0.5	3	7.5	12.5	10	25	5	10	TO-71
2N5566	0.5	3	7.5	12.5	20	50	5	10	TO-71
2N5906	0.6	4.5	70μ	0.25	5	5	5	3	TO-78
2N5908	0.6	4.5	70μ	0.25	10	20	5	5	TO-78
2N5909	0.6	4.5	70μ	0.25	15	40	5	5	TO-78
2N5911	1	5	5	10	10	20	5	5	TO-78
2N5912	1	5	5	10	15	40	5	5	TO-78
2N6485	0.7	4	1	4	15	25	5	5	TO-71
NPDS564	0.5	3	7.5	12.5	5	10	5	5	Mini-Dip
NPDS565	0.5	3	7.5	12.5	10	25	5	10	Mini-Dip
NPDS566	0.5	3	7.5	12.5	20	50	5	10	Mini-Dip
NPDS303	0.5	3.5	1	4	15	t15			Mini-Dip
NPDS404	0.5	2.5	2	7	15	25			SOIC-8
NPDS405	0.5	2.5	2	7	20	40			SOIC-8
NPDS406	0.5	2.5	2	7	40	80			SOIC-8
NPDS5564	0.5	3	7.5	12.5	5	10		5	SOIC-8
NPDS5565	0.5	3	7.5	12.5	10	25		10	SOIC-8
NPDS5566	0.5	3	7.5	12.5	20	50		10	SOIC-8
NPDS5911	1	5	5	10	10	20	5	5	SOIC-8
NPDS5912	1	5	5	10	15	40	5	5	SOIC-8
U257	1	5	5	10	100		15	15	TO-78
U401	0.5	2.5	2	7	5	10			TO-71
U403	0.5	2.5	2	7	10	25			TO-71
U406	0.5	2.5	2	7	40	80			TO-71

t=typical value



3