

30V P-Channel Trench MOSFET(Preliminary)

General Description

- Trench Power technology
- Low R_{DS(ON)}
- Low Gate Charge
- Optimized for fast-switching applications

Applications

- Synchronous Rectification in DC/DC and AC/DC Converters
- Isolated DC/DC Converters in Telecom and Industrial

Product Summary

 V_{DS} -30V I_{D} (at V_{GS} =10V) -90A


 $R_{DS(ON)}$ (at V_{GS} =-10V) < 7.5m Ω

 $R_{DS(ON)}$ (at V_{GS} =-4.5V) < 12m Ω

100% UIS Tested



DFN3x3





Part Number	Package Type	Form	Marking	
TTG90P03ATC	DFN3x3	Tape&Reel	90P03AT	

Absolute Maximum Ratings (T_A =25°C unless otherwise noted)

Parameter		Symbol	Maximum	Units
Drain-Source Voltage		V _{DS}	- 30	V
Gate-Source Voltage		V _{GS}	±20	V
Continuous Drain Current B	T _C =25°C	- I _D	-17	Δ
	T _C =100°C		-17	Α
Pulsed Drain Current ^A		I _{DM}	-270	Α
Avalanche Current ^A		I _{AS}	-30	Α
Single Pulse Avalanche Energy L =0.3mH ^A		E _{AS}	135	mJ
Power Dissipation ^C	T _C =25°C	- P _D	79	W
	T _C =100°C		39.5	W
Junction and Storage Temperature Range		T _J , T _{STG}	-55 to 175	°C

Thermal Characteristics

Parameter		Symbol	Maximum	Units
Maximum Junction-to-Case	Steady-State	$R_{\Theta JC}$	1.9	00.444
Maximum Junction-to-Ambient	Steady-State	R _{OJA}	100	°C/W



		Conditions		Value			
Symbol	Parameter			Min	Тур	Max	Units
STATIC P	ARAMETERS	•					
BV _{DSS}	Drain-Source Breakdown Voltage	I _D =-250μA,V _{GS} =0V		-30			V
			T _J =25°C			-1	
I _{DSS}	Zero Gate Voltage Drain Current	V_{DS} =-30V, V_{GS} =0V	T _J =100°C			-100	μA
I _{GSS}	Gate-Body Leakage Current	$V_{DS} = 0V, V_{GS} = \pm 20V$	1			±100	nA
V _{GS(th)}	Gate Threshold Voltage	V _{DS} =V _{GS} , I _D =-250μA		-1	-1.7	-2.4	V
5		V _{GS} =-10V, I _D =-20A			6.3	7.5	mΩ
R _{DS(ON)}	Static Drain-Source On-Resistance	V _{GS} =-4.5V, I _D =-20A			10	12	mΩ
g _{FS}	Forward Transconductance	V _{DS} =-5V, I _D =-20A			30		S
V _{SD}	Diode Forward Voltage	I _S =-15A, V _{GS} =0V				-1	V
Is	Maximum Body-Diode Continuous Curre	laximum Body-Diode Continuous Current ^B				-17	Α
DYNAMIC	PARAMETERS				•	•	
C _{iss}	Input Capacitance	$V_{GS} = 0V, V_{DS} = -15V, f = 1MH_Z$			4942		pF
C _{oss}	Output Capacitance				473		
C _{rss}	Reverse Transfer Capacitance				461		
SWITCHIN	NG PARAMETERS						
Q _g (10V)	Total Gate Charge	V _{GS} =-10V,V _{DS} =-15V, I _D =-20A			82		
Q_{gs}	Gate Source Charge				14		nC
Q_{gd}	Gate Drain Charge				16		
t _{D(on)}	Turn-On Delay Time	$V_{GS} = -10V, V_{DS} = -15V, I_{D} = -20A,$ $R_{G} = 2.5\Omega$			182		
t _r	Turn-On Rise Time				262		ns
$T_{D(off)}$	Turn-Off Delay Time				1.3		
t _f	Turn-Off Fall Time				9.8		
t _{rr}	Body Diode Reverse Recovery Time	1 - 15A di/d+ 100A	/110		34		ns
Q _{rr}	Body Diode Reverse Recovery Charge	- I _F =-15A, di/dt =100A/μs			79		nC

- A. Single pulse width limited by maximum junction temperature.
- B. The maximum current rating is package limited.
- C. The power dissipation P_D is based on $T_{J(MAX)} = 175$ °C, using junction-to-case thermal resistance, and is more useful in setting the upper dissipation limit for cases where additional heatsinking is used.

Typical Characteristics $T_J = 25^{\circ}\text{C}$, unless otherwise noted




Figure 1: On-Region Characteristics




Figure 2: Transfer Characteristics




Figure 3: On-Resistance vs. Drain Current




Figure 4: Capacitance Characteristics




Figure 5: Gate Charge Characteristics





Figure 6: Body Diode Forward Voltage



 $Z_{\theta\, JC}$ Normalized Transient Thermal Resistance

Wuxi Unigroup Microelectronics CO.,LTD.

Typical Characteristics $T_J = 25^{\circ}C$, unless otherwise noted







Figure 7: On-Resistance vs. Junction Temperature

Figure 8: Vgs(th) vs. Junction Temperature






Figure 11: Normalized Transient Thermal Resistance

Figure 12: Safe Operating Area

-I_D (Amps)



Figure A: Gate Charge Test Circuit and Waveform




Figure B: Resistive Switching Test Circuit and Waveform








Figure C: Unclamped Inductive Switching Test Circuit and Waveform




DFN3×3(捷敏)










avn en ov	DIMENSIONAL REQMTS			
SYMBOL	MIN	NOM	MAX	
A	0.70	0.75	0.80	
b	0.25	0.30	0.35	
С	0.10	0.15	0.25	
D	3.25	3.35	3.45	
D1	3.00	3.10	3.20	
D2	1.78	1.88	1.98	
D3		0.13		
E	3.20	3.30	3.40	
E1	3.00 3.15		3.20	
E2	2.39 2.49		2.59	
е	0.65BSC			
H	0.30	0.39	0.50	
L	0.30	0.40	0.50	
L1		0.13		
θ		10°	12°	
M	* *		0.15	
* Not specified				





Disclaimer

All product specifications and data are subject to change without notice.

For documents and material available from this datasheet, Wuxi Unigroup does not warrant or assume any legal liability or responsibility for the accuracy, completeness of any product or technology disclosed hereunder.

No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document or by any conduct of Wuxi Unigroup.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications. Customers using or selling Wuxi Unigroup products not expressly indicated for use in such applications do so entirely at their own risk and agree to fully indemnify Wuxi Unigroup for any damages arising or resulting from such use or sale.

Wuxi Unigroup disclaims any and all liability arising out of the use or application of any product described herein or of any information provided herein to the maximum extent permitted by law. The product specifications do not expand or otherwise modify Wuxi Unigroup's terms and conditions of purchase, including but not limited to the warranty expressed therein, which apply to these products.

Wuxi Unigroup Microelectronics CO., LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.

In the event that any or all Wuxi Unigroup products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.

Information (including circuit diagrams and circuit parameters) herein is for example only. It is not guaranteed for volume production. Wuxi Unigroup believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.