

## POWER TRANSFORMER **CHASSIS MOUNT : Isolation**

# N-66A

#### Electrical Specifications (@25°C)

- 1. Maximum Power:
- 2. Input Voltage:

Parallel: 115V@50/60Hz

- Series:230V@50/60Hz
- 3. Output Voltage:
- 115V + 5% 4. Full Secondary Load: 2.17 Amps RMS
- 5. Voltage Regulation: 5 % TYP @ full load to no load

250 VA

#### **Description:**

The N-66A is a power transformer for isolating equipment from direct connection to the powerline. The primary and secondary coils are concentrically wound providing excellent magnetic coupling. Having good magnetic coupling between windings helps reduce leakage flux and phase shift.

#### Safety:


These units are designed with 1500V isolation between winding to winding and between winding and core. Materials and construction are rated for Class B insulation system.

Dimensions:				Unit: In inches	
А	В	С	D	Е	F
4.625	3.937	4.625	3.00	3.625	2.250

Weight: 11.0 Lbs.

Mounting Holes: .375 x .187" Connections: 10.0±1" leads, 0.250±0.062" Skin & Tin

### Schematic:



INPUT - Series: BLK to BRN, JUMPER YEL to BLU Parallel: BLK to YEL, JUMPER BLK to BLU and YEL to BRN OUTPUT: RED to RED

SHIELD: WHT


RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.


\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571









Publish Date: May 31, 2019