

ZENER DIODES

Zener Type No.	Zener Voltage at I_{ZT}		Max. Zener Impedance @ I_{ZT} Ohms	Zener Voltage Tolerance	Power Rating	Device Package
	Volts	@ mA				
1N957	6.8	18.5	4.5	No Suffix = 20% Suffix A = 10% Suffix B = 5%	400mw	DO-7
1N958	7.5	16.5	5.5			
1N959	8.2	15.0	6.5			
1N960	9.1	14.0	7.5	" "	"	"
1N961	10.0	12.5	8.5	" "	"	"
1N962	11.0	11.5	9.5	" "	"	"
1N963	12.0	10.5	11.5	" "	"	"
1N964	13.0	9.5	13.0	" "	"	"
1N965	15.0	8.5	16.0	" "	"	"
1N966	16.0	7.8	17.0	" "	"	"
1N967	18.0	7.0	21.0	" "	"	"
1N968	20.0	6.2	25.0	" "	"	"
1N969	22.0	5.6	29.0	" "	"	"
1N970	24.0	5.2	33.0	" "	"	"
1N971	27.0	4.6	41.0	" "	"	"
1N972	30.0	4.2	49.0	" "	"	"
1N973	33.0	3.8	58.0	" "	"	"
1N974	36.0	3.4	70.0	" "	"	"
1N975	39.0	3.2	80.0	" "	"	"
1N976	43.0	3.0	93.0	" "	"	"
1N977	47.0	2.7	105.0	" "	"	"
1N978	51.0	2.5	125.0	" "	"	"
1N979	56.0	2.2	150.0	" "	"	"
1N980	62.0	2.0	185.0	" "	"	"
1N981	68.0	1.8	230.0	" "	"	"
1N982	75.0	1.7	270.0	" "	"	"
1N983	82.0	1.5	330.0	" "	"	"
1N984	91.0	1.4	400.0	" "	"	"
1N985	100.0	1.3	500.0	" "	"	"
1N986	110.0	1.1	750.0	" "	"	"
1N746	3.3	20.0	28.0	No Suffix = 10% Suffix A = 5%	400mw	DO-7
1N747	3.6	20.0	24.0			
1N748	3.9	20.0	23.0			
1N749	4.3	20.0	22.0	" "	"	"
1N750	4.7	20.0	19.0	" "	"	"
1N751	5.1	20.0	17.0	" "	"	"
1N752	5.6	20.0	11.0	" "	"	"
1N753	6.2	20.0	7.0	" "	"	"