



## 90 MHz Crystal Bandstop Filter

Part Number: AM90CR213

| Filter Type                 | Crystal Bandpass        |
|-----------------------------|-------------------------|
| Center Frequency (Fo)       | 90 MHz                  |
| 3 dB Band Width:            | 30 KHz Nom              |
| Insertion Loss:             | 6 dB Max                |
| Pass Band Return Loss: @ Fo | 15 dB Min, 25 dB Target |
| 60 dBc Band Width:          | ±85 KHz Max             |
| Input Power                 | 3dBm Max                |
| Impedance:                  | 50 Ohms                 |
| Operating Temperature:      | TBD                     |
| Workmanship                 | IPC-610 Class 2         |
| RoHS COMPLIANT              | NO                      |

### Mechanical Package Style: "FF"

