

Low Level and General Purpose Amplifiers

TYPE NO.	POLARITY	CASE	MAXIMUM RATINGS			H _{FE}				V _{CE(sat)}		f _T (MHz)	C _{ob} (MHz)	N.F. (dB)
			P _d (mW)	I _C (mA)	V _{CEO} (V)	min	max	I _C (mA)	V _{CE} (V)	max (V)	I _C (mA)			
BC267	N	TO-18	400	1000	45	110	450 #	2	5	0.3	100	150	8.6+	3+
BC268	N	TO-18	400	1000	20	110	800 #	2	5	0.3	100	150	8.6+	3+
BC269	N	TO-18	400	1000	30	220	800 #	2	5	0.3	100	150	8.6+	4
BC280	N	TO-18	360	100	40	180	600 #	1	5	0.7	10	-	2.8+	3
BC282	N	TO-18	400	600	30	50	300	50	5	1	300	100	10	-
BC283	P	TO-18	400	600	30	40	270	50	5	1	300	80+	7	-
BC307	P	TO-92F	300	100	45	70	450 #	2	5	0.3	10	100	6	10
BC308	P	TO-92F	300	100	25	70	800 #	2	5	0.3	10	100	6	10
BC309	P	TO-92F	300	100	20	200	800 #	2	5	0.3	10	100	6	4
BC315	P	TO-92F	300	100	35	100	350 #	2	5	0.6	100	200	5+	2
BC315L	P	TO-92B	300	100	35	100	350 #	2	5	0.6	100	200	5+	2
BC317	N	TO-92A	310	150	45	110	450 #	2	5	0.5	100	100	4	6
BC318	N	TO-92A	310	150	30	110	800 #	2	5	0.5	100	100	7	6
BC319	N	TO-92A	310	150	20	200	800 #	2	5	0.5	100	100	4	6
BC320	P	TO-92A	310	150	45	70	450 #	2	5	0.3	10	100	4	6
BC321	P	TO-92A	310	150	30	70	800 #	2	5	0.3	10	100	4	6
BC322	P	TO-92A	310	150	20	200	800 #	2	5	0.3	10	100	4	4
BC326	P	TO-18	360	50	60	100	500	0.01	5	0.35	1	60	9	-
BC330	N	TO-92F	250	30	45	220	- #	2	5	1	10	100	3	2
BC332	N	TO-92F	250	30	45	100	- #	2	5	1	10	100	3	6
BC333	N	TO-92F	310	50	25	100	1000 #	0.1	5	0.6	10	50	4	-
BC334	P	TO-92F	310	50	25	100	1000 #	0.1	5	0.6	10	50	4	-
BC335	N	TO-92F	310	50	25	100	1000 #	0.1	5	0.6	10	50	4	-
BC336	P	TO-92F	310	50	25	100	1000 #	0.1	5	0.6	10	50	4	-
BC347	N	TO-92A	300	100	45	40	450 #	2	5	0.25	10	125	4	10
BC348	N	TO-92A	300	100	30	40	450 #	2	5	0.25	10	125	4	10
BC349	N	TO-92A	300	100	20	40	450 #	2	5	0.25	10	125	4	10
BC350	N	TO-92A	300	100	45	40	450 #	2	5	0.25	10	125	4	10
BC351	P	TO-92A	300	100	30	40	450 #	2	5	0.25	10	125	4	10
BC352	P	TO-92A	300	100	20	40	450 #	2	5	0.25	10	125	4	10
BC357	P	TO-92F	310	100	25	100	500	10	10	0.25	10	200	10	-
BC358	N	TO-92F	310	100	25	100	500	10	10	0.25	10	125	10	-
BC382	N	TO-92F	300	100	45	100	900 #	2	5	0.6	100	150	5	6
BC382L	N	TO-92B	300	100	45	100	900 #	2	5	0.6	100	150	5	6
BC383	N	TO-92F	300	100	30	100	900 #	2	5	0.6	100	150	5	6
BC383L	N	TO-92B	300	100	30	100	900 #	2	5	0.6	100	150	5	6
BC384	N	TO-92F	300	100	30	250	900 #	2	5	0.6	100	150	5	4
BC384L	N	TO-92B	300	100	30	250	900 #	2	5	0.6	100	150	5	4
BC385	N	TO-92F	300	100	45	100	480	2	5	0.6	100	150	5	-
BC386	N	TO-92F	300	100	20	100	850	2	5	0.6	100	150	5	-
BC413	N	TO-92F	300	100	30	180	800 #	2	5	0.6	100	200+	2.7+	2.5
BC414	N	TO-92F	300	100	45	180	800 #	2	5	0.6	100	200+	2.7+	2.5
BC415	P	TO-92F	300	100	35	120	800 #	2	5	0.6	100	200+	2.7+	2
BC416	P	TO-92F	300	100	45	120	800 #	2	5	0.6	100	200+	2.7+	2
BC447	N	TO-92F	625	300	80	50	460 #	2	5	0.25	100	100	-	-
BC448	P	TO-92F	625	300	80	50	460 #	2	5	0.25	100	100	-	-
BC449	N	TO-92F	625	300	100	50	460 #	2	5	0.25	100	100	-	-
BC451	N	TO-92F	300	100	45	110	800 #	2	6	-	-	150	4.5	10
BC452	N	TO-92F	300	100	30	110	800 #	2	6	-	-	150	4.5	10
BC453	N	TO-92F	300	100	30	110	800 #	2	6	-	-	150	4.5	4
BC454	P	TO-92F	300	100	45	125	800 #	2	6	-	-	150	6	10
BC455	P	TO-92F	300	100	30	125	800 #	2	6	-	-	150	6	10
BC456	P	TO-92F	300	100	30	125	800 #	2	6	-	-	150	6	4
BC478	P	TO-18	360	150	50	110	450 #	2	5	0.25	10	-	6	6
BC479	P	TO-18	360	150	40	220	450 #	2	5	0.25	10	-	6	4

HFE groupings available □ hfe @ 1KHz + typical value