

Glass passivated Single Phase Bridge Rectifiers Reverse Voltage 50~1000V Output Current 4.0A

#### **Features**

- ♦ Ideal for printed circuit boards
- ♦ High surge current capability
- ♦ High case dielectric strength of 1500V<sub>RMS</sub>
- ♦ Solder dip 260 °C, 40 s

#### **Mechanical Data**

◆ Case:GBU

Expoxy meers UL-94V-0 Flammability rating

- ◆ Teminals:Matte tin plated(E3 Suffix) leads,solderable per J-STD-002B and JESD22-B102D
- ♦ Polarity:As marked on body
- ◆ Mounting torquw:10 cm-kg (8.8 inches-lbs) max.
- ◆ Recommended Torque:5.7 cm-kg (5 inches-lbs)

## **Typical Applications**

General purpose use in ac-to-dc bridge full wave rectification for Monitor, TV, Printer, Switching Mode Power Supply, Adapter, Audio equipment, and Home Appliances applications.

Maximum Ratings (TA = 25 °C unless otherwise noted)									
Parameter	Symbol	GBU4A	GBU4B	GBU4D	GBU4G	GBU4J	GBU4K	GBU4M	Unit
Maximum repetitive peak reverse voltage	VRRM	50	100	200	400	600	800	1000	V
Maximum RMS voltage	VRMS	35	70	140	280	420	560	700	V
Maximum DC blocking voltage	VDC	50	100	200	400	600	800	1000	V
Maximum average forward $T_c=100^{\circ}C^{\circ}$ rectified output current at $T_A=40^{\circ}C^{\circ}$	IF(AV)	3.0					Α		
Peak forward surge current 8.3 ms single half sine-wave superimposed on rated load	IFSM	150					Α		
Rating for fusing(t<8.3ms)	I <sup>2</sup> t	93				A <sup>2</sup> sec			
Operating junction and storage temperature range	TJ, TSTG	- 55 to + 150					°C		

Electrical Characteristics (TA = 25 °C unless otherwise noted)											
Parameter	Test Conditions	Symbol	GBU4A	GBU4B	GBU4D	GBU4G	GBU4J	GBU4K	GBU4M	Unit	
Maximum instantaneous f drop per leg at 2.0A	V <sub>F</sub>	1.00							Volts		
Maximum DC reverse		5.0							μA		
current at rated DC blocking voltage per leg	TA=125℃	I <sub>R</sub>				500	500				
Typical junction capacitance per leg	4.0 V, 1 MHz	Сл	100 45					pF			

Thermal Characteristics										
Parameter	Symbol	GBU4A	GBU4B	GBU4D	GBU4G	GBU4J	GBU4K	GBU4M	Unit	
Typical thermal resistance per leg	R <sub>eJA</sub> <sup>(2)</sup>	22							°C/W	
	R <sub>eJC</sub> <sup>(1,3)</sup>	4.2								

Notes: 1. Unit case mounted on 5.1\*5.1\*0.15 cm thick AL plate heatsink

- 2. Units mounted in free air, no heatsink on P.C.B. with 0.5\*0.5" (12.7\*12.7mm) copper pads and 0.375"(9.5mm) lead length
- 3. Recommended mounting position is to bolt down on heatsink with silicone thermal compound for maximum heat transfer with #6 screws

Glass passivated Single Phase Bridge Rectifiers Reverse Voltage 50~1000V Output Current 4.0A

## Ratings and Characteristics Curves

 $(TA = 25^{\circ}C \text{ unless otherwise noted})$ 




Figure 1. Derating Curve Output Rectified Current




Figure 3. Typical Forward Characteristics Per Leg




Figure 4. Typical Reverse Leakage Characteristics Per Leg




Figure 2. Maximum Non-Repetitive Peak Forward Surge Current Per Leg




Figure 5. Typical Junction Capacitance Per Leg





Figure 6. Typical Transient Thermal Impedance


www.goodark.com 2/4 2019.01-Rev.B



Glass passivated Single Phase Bridge Rectifiers Reverse Voltage 50~1000V Output Current 4.0A

## **Package Outline Dimensions**







Glass passivated Single Phase Bridge Rectifiers Reverse Voltage 50~1000V Output Current 4.0A

#### **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.

www.goodark.com 4/4 2019.01-Rev.B