

UT3401

Power MOSFET


P-CHANNEL ENHANCEMENT
MODE POWER MOSFET

■ DESCRIPTION

The UTC UT3401 is P-channel enhancement mode Power MOSFET, designed with high density cell, with fast switching speed, low on-resistance, excellent thermal and electrical capabilities and operation with low gate voltages.

This device is suitable for use as a load switch or in PWM applications.


■ SYMBOL




■ ORDERING INFORMATION

Ordering Number		Package	Pin Assignment						Packing
Lead Free	Halogen Free		1	2	3	4	5	6	
UT3401L-AE3-R	UT3401G-AE3-R	SOT-23	G	S	D	-	-	-	Tape Reel
UT3401L-AG6-R	UT3401G-AG6-R	SOT-26	D	D	G	S	D	D	Tape Reel

Note: Pin Assignment: G: Gate S: Source D: Drain

UT3401G-AE3-R 	(1)Packing Type (2)Package Type (3)Green Package	(1) R: Tape Reel (2) AE3: SOT-23, AG6: SOT-26 (3) G: Halogen Free and Lead Free, L: Lead Free
--	--	---

■ MARKING



■ ABSOLUTE MAXIMUM RATINGS ($T_A=25^\circ\text{C}$, unless otherwise specified)

PARAMETER	SYMBOL	RATINGS	UNIT
Drain-Source Voltage	V_{DSS}	-30	V
Gate-Source Voltage	V_{GS}	± 12	V
Continuous Drain Current (Note 1)	I_D	-4.2	A
Pulsed Drain Current (Note 2)	I_{DM}	-30	A
Power Dissipation (Note 1)	P_D	1.25	W
Junction Temperature	T_J	+150	$^\circ\text{C}$
Storage Temperature	T_{STG}	-55 ~ +150	$^\circ\text{C}$

Note: Absolute maximum ratings are those values beyond which the device could be permanently damaged.

Absolute maximum ratings are stress ratings only and functional device operation is not implied.

■ THERMAL DATA

PARAMETER	SYMBOL	RATINGS	UNIT
Junction-to-Ambient	θ_{JA}	100	$^\circ\text{C}/\text{W}$

Notes: Surface mounted on 1 in² copper pad of FR4 board with 2oz. Copper, in a still air environment with $T_A=25^\circ\text{C}$.

■ ELECTRICAL CHARACTERISTICS ($T_A=25^\circ\text{C}$, unless otherwise specified)







PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
OFF CHARACTERISTICS						
Drain-Source Breakdown Voltage	BV_{DSS}	$I_D=-250\mu\text{A}, V_{GS}=0\text{V}$	-30			V
Drain-Source Leakage Current	I_{DSS}	$V_{DS}=-24\text{V}, V_{GS}=0\text{V}$			-1	μA
Gate-Source Leakage Current	I_{GSS}	$V_{DS}=0\text{V}, V_{GS}=\pm 12\text{V}$			± 100	nA
ON CHARACTERISTICS						
Gate Threshold Voltage	$V_{GS(\text{TH})}$	$V_{DS}=V_{GS}, I_D=-250\mu\text{A}$	-0.7	-1.0	-1.3	V
		$V_{GS}=-10\text{V}, I_D=-4.2\text{A}$		42	50	$\text{m}\Omega$
Drain-Source On-State Resistance (Note 2)	$R_{DS(\text{ON})}$	$V_{GS}=-4.5\text{V}, I_D=-4\text{A}$		53	65	$\text{m}\Omega$
		$V_{GS}=-2.5\text{V}, I_D=-1\text{A}$		80	120	$\text{m}\Omega$
DYNAMIC PARAMETERS						
Input Capacitance	C_{ISS}	$V_{GS}=0\text{V}, V_{DS}=-15\text{V}, f=1\text{MHz}$		925		pF
Output Capacitance	C_{OSS}			125		pF
Reverse Transfer Capacitance	C_{RSS}			110		pF
SWITCHING PARAMETERS						
Total Gate Charge (Note 2)	Q_G	$V_{DS}=-15\text{V}, V_{GS}=-4.5\text{V}, I_D=-4\text{A}$		14.2		nC
Gate-Source Charge	Q_{GS}			3.5		nC
Gate-Drain Charge	Q_{GD}			3		nC
Turn-ON Delay Time (Note 2)	$t_{D(\text{ON})}$	$V_{DS}=-15\text{V}, V_{GS}=-10\text{V}, I_D=-4\text{A}$		7		ns
Turn-ON Rise Time	t_R			15		ns
Turn-OFF Delay Time	$t_{D(\text{OFF})}$			55		ns
Turn-OFF Fall Time	t_F			24		ns
SOURCE- DRAIN DIODE RATINGS AND CHARACTERISTICS						
Maximum Continuous Drain-Source Diode Forward Current	I_S				-2.2	A
Drain-Source Diode Forward Voltage (Note 2)	V_{SD}	$V_{DS}=0\text{V}, I_S=-1\text{A}$		-0.75	-1	V
Reverse Recovery Time	t_{rr}	$I_F=-4\text{A}, dI/dt=100\text{A}/\mu\text{s}$		200		ns
Reverse Recovery Charge	Q_{rr}			400		nC

Notes: 1. Repetitive Rating : Pulse width limited by maximum junction temperature.







2. Pulse width $\leq 300\mu\text{s}$, duty cycle $\leq 2\%$.

3. Surface mounted on 1 in² copper pad of FR4 board with 2oz. Copper, in a still air environment with $T_A=25^\circ\text{C}$.


■ TYPICAL CHARACTERISTICS



■ TYPICAL CHARACTERISTICS (Cont.)



- TYPICAL CHARACTERISTICS (Cont.)



Note: Surface mounted on 1 in² copper pad of FR4 board with 2oz.

UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. UTC reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.