

#### PART OBSOLETE - USE MMDT3946-7-F



**MMDT4146** 

#### COMPLEMENTARY NPN / PNP SMALL SIGNAL SURFACE MOUNT TRANSISTOR

#### **Features**

- Complementary Pair One 4124-Type NPN One 4126-Type PNP
- **Epitaxial Planar Die Construction**
- Ideal for Medium Power Amplification and Switching
- Ultra-Small Surface Mount Package
- Lead Free/RoHS Compliant (Note 3)
- "Green" Device (Note 4 and 5)

### **Mechanical Data**

- Case: SOT-363
- Case Material: Molded Plastic, "Green" Molding Compound, Note 5. UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020D
- Terminals: Matte Tin Finish annealed over Alloy 42 leadframe (Lead Free Plating) Solderable per MIL-STD-202, Method 208
- Terminal Connections: See Diagram
- Marking Information: See Page 4
- Ordering Information: See Page 4
- Weight: 0.006 grams (approximate)





# E1, B1, C1 = PNP4126 Section E2, B2, C2 = NPN4124 Section

Device Schematic

#### Maximum Ratings, NPN 4124 Section @TA = 25°C unless otherwise specified

Characteristic	Symbol	Value	Unit
Collector-Base Voltage	$V_{CBO}$	30	V
Collector-Emitter Voltage	$V_{CEO}$	25	V
Emitter-Base Voltage	$V_{EBO}$	5.0	V
Collector Current – Continuous (Note 1)	lc	200	mA

## Maximum Ratings, PNP 4126 Section @TA = 25°C unless otherwise specified

Characteristic	Symbol	Value	Unit
Collector-Base Voltage	$V_{CBO}$	-25	V
Collector-Emitter Voltage	$V_{\sf CEO}$	-25	V
Emitter-Base Voltage	$V_{EBO}$	-4	V
Collector Current - Continuous (Note 1)	lc	-200	mA

### Thermal Characteristics – Total Device

Characteristic		Symbol	Value	Unit
Power Dissipation	(Note 1, 2)	$P_{D}$	200	mW
Thermal Resistance, Junction to Ambient	(Note 1)	$R_{\rm eJA}$	625	°C/W

Notes:

- Device mounted on FR-4 PCB, 1 inch x 0.85 inch x 0.062 inch; pad layout as shown on Diodes Inc. suggested pad layout document AP02001, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.
- Maximum combined dissipation.
- No purposefully added lead.
- Diodes Inc.'s "Green" policy can be found on our website at http://www.diodes.com/products/lead\_free/index.php.
- Product manufactured with Date Code UO (week 40, 2007) and newer are built with Green Molding Compound. Product manufactured prior to Date Code UO are built with Non-Green Molding Compound and may contain Halogens or Sb2O3 Fire Retardants.



# Electrical Characteristics, NPN 4124 Section @TA = 25°C unless otherwise specified


Characteristic	Symbol	Min	Max	Unit	Test Condition
OFF CHARACTERISTICS (Note 6)				•	
Collector-Base Breakdown Voltage	V <sub>(BR)CBO</sub>	30	_	V	$I_C = 10\mu A, I_E = 0$
Collector-Emitter Breakdown Voltage	V <sub>(BR)CEO</sub>	25	_	V	I <sub>C</sub> = 1.0mA, I <sub>B</sub> = 0
Emitter-Base Breakdown Voltage	V <sub>(BR)EBO</sub>	5.0	_	V	$I_E = 10 \mu A, I_C = 0$
Collector Cutoff Current	I <sub>CBO</sub>		50	nA	$V_{CB} = 20V, I_{E} = 0V$
Emitter Cutoff Current	I <sub>EBO</sub>	_	50	nA	V <sub>EB</sub> = 3.0V, I <sub>C</sub> = 0V
ON CHARACTERISTICS (Note 6)					
DC Current Gain	h	120	360		I <sub>C</sub> = 2.0mA, V <sub>CE</sub> = 1.0V
De Garrent Gain	h <sub>FE</sub>	60	—		$I_C = 50 \text{mA}, V_{CE} = 1.0 \text{V}$
Collector-Emitter Saturation Voltage	V <sub>CE(SAT)</sub>		0.30	V	$I_C = 50mA$ , $I_B = 5.0mA$
Base-Emitter Saturation Voltage	$V_{BE(SAT)}$		0.95	V	$I_C = 50mA$ , $I_B = 5.0mA$
SMALL SIGNAL CHARACTERISTICS					
Output Capacitance	$C_{obo}$	_	4.0	pF	$V_{CB} = 5.0V$ , $f = 1.0MHz$ , $I_E = 0$
Input Capacitance	Cibo		8.0	pF	$V_{EB} = 0.5V$ , $f = 1.0MHz$ , $I_{C} = 0$
Small Signal Current Gain	h <sub>fe</sub>	120	480	_	$V_{CE}$ = 1.0V, $I_{C}$ = 2.0mA, $f$ = 1.0kHz
Current Gain-Bandwidth Product	f <sub>T</sub>	300	_	MHz	V <sub>CE</sub> = 20V, I <sub>C</sub> = 10mA, f = 100MHz
Noise Figure	NF		5.0	dB	$V_{CE}$ = 5.0V, $I_{C}$ = 100μA, $R_{S}$ = 1.0kΩ, $f$ = 1.0kHz


# Electrical Characteristics, PNP 4126 Section @TA = 25°C unless otherwise specified

Characteristic	Symbol	Min	Max	Unit	Test Condition
OFF CHARACTERISTICS (Note 6)					
Collector-Base Breakdown Voltage	V <sub>(BR)CBO</sub>	-25	_	V	$I_{C} = -10\mu A, I_{E} = 0$
Collector-Emitter Breakdown Voltage	V <sub>(BR)CEO</sub>	-25	_	V	I <sub>C</sub> = -1.0mA, I <sub>B</sub> = 0
Emitter-Base Breakdown Voltage	V <sub>(BR)EBO</sub>	-4.0	_	V	$I_E = -10\mu A, I_C = 0$
Collector Cutoff Current	I <sub>CBO</sub>	_	-50	nA	V <sub>CB</sub> = -20V, I <sub>E</sub> = 0V
Emitter Cutoff Current	I <sub>EBO</sub>	_	-50	nA	$V_{EB} = -3.0V, I_{C} = 0V$
ON CHARACTERISTICS (Note 6)					
DC Current Gain	h <sub>FE</sub>	120	360		$I_C = -2.0 \text{mA}, V_{CE} = -1.0 \text{V}$
DC Current Gain		60	_		$I_C = -50 \text{mA}, V_{CE} = -1.0 \text{V}$
Collector-Emitter Saturation Voltage	V <sub>CE(SAT)</sub>	_	-0.40	V	$I_C = -50 \text{mA}, I_B = -5.0 \text{mA}$
Base-Emitter Saturation Voltage	V <sub>BE(SAT)</sub>	_	-0.95	V	$I_C = -50 \text{mA}, I_B = -5.0 \text{mA}$
SMALL SIGNAL CHARACTERISTICS					
Output Capacitance	$C_{obo}$	_	4.5	pF	$V_{CB} = -5.0V$ , $f = 1.0MHz$ , $I_E = 0$
Input Capacitance	C <sub>ibo</sub>	_	10	pF	$V_{EB} = -0.5V$ , $f = 1.0MHz$ , $I_C = 0$
Small Signal Current Gain	h <sub>fe</sub>	120	480	_	$V_{CE} = -1.0V$ , $I_{C} = -2.0mA$ , $f = 1.0kHz$
Current Gain-Bandwidth Product	f <sub>T</sub>	250	_	MHz	$V_{CE} = -20V, I_{C} = -10mA,$ f = 100MHz
Noise Figure	NF	_	4.0	dB	$V_{CE}$ = -5.0V, $I_{C}$ = -100μA, $R_{S}$ = 1.0kΩ, $f$ = 1.0kHz

Notes: 6. Short duration pulse test used to minimize self-heating effect.










Fig. 3 Typical Collector-Emitter Saturation Voltage vs. Collector Current (PNP-4126)





Fig. 5 Typical Capacitance Characteristics (PNP-4126)









Fig. 4 Typical Base-Emitter Saturation Voltage vs. Collector Current (PNP-4126)









V<sub>R</sub>, REVERSE VOLTAGE (V) Fig. 9 Typical Capacitance Characteristics (NPN-4124)

# $V_{\text{BE(SAT)}}$ , BASE-EMITTER SATURATION VOLTAGE (V) 0.1 1,000 10 I<sub>C</sub>, COLLECTOR CURRENT (mA) Fig. 8 Typical Base-Emitter Saturation Voltage

vs. Collector Current (NPN-4124)


# Ordering Information (Note 7)

Part Number	Case	Packaging
MMDT4146-7-F	SOT-363	3000/Tape & Reel

7. For packaging details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf. Notes:

# **Marking Information**

0.1




K12 = Product Type Marking Code YM = Date Code Marking Y = Year (ex: N = 2002) M = Month (ex: 9 = September)

Date Code Key

Year	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015
Code	J	K	Г	М	N	Р	R	S	Т	С	V	W	Χ	Υ	Z	Α	В	С
Month	Jan		Feb	Mai	·	Apr	May	,	Jun	Jul		Aug	Sep		Oct	Nov	,	Dec
Code	1		2	3		4	5		6	7		8	9		0	N		D




# **Package Outline Dimensions**



	SOT-363							
Dim	Min	Max						
Α	0.10	0.30						
В	1.15	1.35						
С	2.00	2.20						
D	0.65 Typ							
F	0.40	0.45						
Н	1.80	2.20						
J	0	0.10						
K	0.90	1.00						
L	0.25	0.40						
М	0.10	0.22						
α	0°	8°						
All Di	All Dimensions in mm							

# **Suggested Pad Layout**



Dimensions	Value (in mm)
Z	2.5
G	1.3
Х	0.42
Y	0.6
C1	1.9
C2	0.65



#### **IMPORTANT NOTICE**

- DIODES INCORPORATED AND ITS SUBSIDIARIES ("DIODES") MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO ANY INFORMATION CONTAINED IN THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).
- 2. The Information contained herein is for informational purpose only and is provided only to illustrate the operation of Diodes products described herein and application examples. Diodes does not assume any liability arising out of the application or use of this document or any product described herein. This document is intended for skilled and technically trained engineering customers and users who design with Diodes products. Diodes products may be used to facilitate safety-related applications; however, in all instances customers and users are responsible for (a) selecting the appropriate Diodes products for their applications, (b) evaluating the suitability of the Diodes products for their intended applications, (c) ensuring their applications, which incorporate Diodes products, comply the applicable legal and regulatory requirements as well as safety and functional-safety related standards, and (d) ensuring they design with appropriate safeguards (including testing, validation, quality control techniques, redundancy, malfunction prevention, and appropriate treatment for aging degradation) to minimize the risks associated with their applications.
- Diodes assumes no liability for any application-related information, support, assistance or feedback that may be provided by Diodes from time to time. Any customer or user of this document or products described herein will assume all risks and liabilities associated with such use, and will hold Diodes and all companies whose products are represented herein or on Diodes' websites, harmless against all damages and liahilities
- Products described herein may be covered by one or more United States, international or foreign patents and pending patent applications. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks and trademark applications. Diodes does not convey any license under any of its intellectual property rights or the rights of any third parties (including third parties whose products and services may be described in this document or on Diodes' website) under this document.
- Diodes' provided subject to Standard Terms (https://www.diodes.com/about/company/terms-and-conditions/terms-and-conditions-of-sales/) or other applicable terms. This document does not alter or expand the applicable warranties provided by Diodes. Diodes does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel.
- Diodes products and technology may not be used for or incorporated into any products or systems whose manufacture, use or sale is prohibited under any applicable laws and regulations. Should customers or users use Diodes products in contravention of any applicable laws or regulations, or for any unintended or unauthorized application, customers and users will (a) be solely responsible for any damages, losses or penalties arising in connection therewith or as a result thereof, and (b) indemnify and hold Diodes and its representatives and agents harmless against any and all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim relating to any noncompliance with the applicable laws and regulations, as well as any unintended or unauthorized application.
- While efforts have been made to ensure the information contained in this document is accurate, complete and current, it may contain technical inaccuracies, omissions and typographical errors. Diodes does not warrant that information contained in this document is error-free and Diodes is under no obligation to update or otherwise correct this information. Notwithstanding the foregoing, Diodes reserves the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes.
- Any unauthorized copying, modification, distribution, transmission, display or other use of this document (or any portion hereof) is prohibited. Diodes assumes no responsibility for any losses incurred by the customers or users or any third parties arising from any such unauthorized use.

Copyright © 2021 Diodes Incorporated

www.diodes.com